Internal Use Only

North/Latin America http://aic.lgservice.com
Europe/Africa http://eic.lgservice.com
Asia/Oceania http://biz.lgservice.com

LED LCD TV
SERVICE MANUAL

CHASSIS : LJ01U

MODEL : 32LV2500 32LV2500-SA

CAUTION
BEFORE SERVICING THE CHASSIS,
READ THE SAFETY PRECAUTIONS IN THIS MANUAL.



P/NO : MFL62886932 (1103-REV01)

Printed in Korea

CONTENTS

CONTENTS 2

SAFETY PRECAUTIONS 3

SPECIFICATION 6

ADJUSTMENT INSTRUCTION..... 11

EXPLODED VIEW 16

SVC. SHEET .....

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

SAFETY PRECAUTIONS

IMPORTANT SAFETY NOTICE

Many electrical and mechanical parts in this chassis have special safety-related characteristics. These parts are identified by ⚠ in the Schematic Diagram and Exploded View.
It is essential that these special safety parts should be replaced with the same components as recommended in this manual to prevent Shock, Fire, or other Hazards.
Do not modify the original design without permission of manufacturer.

General Guidance

An **isolation Transformer should always be used** during the servicing of a receiver whose chassis is not isolated from the AC power line. Use a transformer of adequate power rating as this protects the technician from accidents resulting in personal injury from electrical shocks.

It will also protect the receiver and it's components from being damaged by accidental shorts of the circuitry that may be inadvertently introduced during the service operation.

If any fuse (or Fusible Resistor) in this TV receiver is blown, replace it with the specified.

When replacing a high wattage resistor (Oxide Metal Film Resistor, over 1W), keep the resistor 10mm away from PCB.

Keep wires away from high voltage or high temperature parts.

Before returning the receiver to the customer,

always perform an **AC leakage current check** on the exposed metallic parts of the cabinet, such as antennas, terminals, etc., to be sure the set is safe to operate without damage of electrical shock.

Leakage Current Cold Check(Antenna Cold Check)
With the instrument AC plug removed from AC source, connect an electrical jumper across the two AC plug prongs. Place the AC switch in the on position, connect one lead of ohm-meter to the AC plug prongs tied together and touch other ohm-meter lead in turn to each exposed metallic parts such as antenna terminals, phone jacks, etc.
If the exposed metallic part has a return path to the chassis, the measured resistance should be between 1MΩ and 5.2MΩ.
When the exposed metal has no return path to the chassis the reading must be infinite.
An other abnormality exists that must be corrected before the receiver is returned to the customer.

Leakage Current Hot Check (See below Figure)
Plug the AC cord directly into the AC outlet.

Do not use a line Isolation Transformer during this check.
Connect 1.5K/10watt resistor in parallel with a 0.15uF capacitor between a known good earth ground (Water Pipe, Conduit, etc.) and the exposed metallic parts.
Measure the AC voltage across the resistor using AC voltmeter with 1000 ohms/volt or more sensitivity.
Reverse plug the AC cord into the AC outlet and repeat AC voltage measurements for each exposed metallic part. Any voltage measured must not exceed 0.75 volt RMS which is corresponds to 0.5mA.
In case any measurement is out of the limits specified, there is possibility of shock hazard and the set must be checked and repaired before it is returned to the customer.

Leakage Current Hot Check circuit



Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

SERVICING PRECAUTIONS

CAUTION: Before servicing receivers covered by this service manual and its supplements and addenda, read and follow the *SAFETY PRECAUTIONS* on page 3 of this publication.
NOTE: If unforeseen circumstances create conflict between the following servicing precautions and any of the safety precautions on page 3 of this publication, always follow the safety precautions. Remember: Safety First.

General Servicing Precautions

1. Always unplug the receiver AC power cord from the AC power source before;
   a. Removing or reinstalling any component, circuit board module or any other receiver assembly.
   b. Disconnecting or reconnecting any receiver electrical plug or other electrical connection.
   c. Connecting a test substitute in parallel with an electrolytic capacitor in the receiver.
   CAUTION: A wrong part substitution or incorrect polarity installation of electrolytic capacitors may result in an explosion hazard.

2. Test high voltage only by measuring it with an appropriate high voltage meter or other voltage measuring device (DVM, FETVOM, etc) equipped with a suitable high voltage probe.
   Do not test high voltage by "drawing an arc".
3. Do not spray chemicals on or near this receiver or any of its assemblies.
4. Unless specified otherwise in this service manual, clean electrical contacts only by applying the following mixture to the contacts with a pipe cleaner, cotton-tipped stick or comparable non-abrasive applicator; 10% (by volume) Acetone and 90% (by volume) isopropyl alcohol (90%-99% strength)
   CAUTION: This is a flammable mixture.
   Unless specified otherwise in this service manual, lubrication of contacts in not required.
5. Do not defeat any plug/socket B+ voltage interlocks with which receivers covered by this service manual might be equipped.
6. Do not apply AC power to this instrument and/or any of its electrical assemblies unless all solid-state device heat sinks are correctly installed.
7. Always connect the test receiver ground lead to the receiver chassis ground before connecting the test receiver positive lead.
   Always remove the test receiver ground lead last.
8. *Use with this receiver only the test fixtures specified in this service manual.*
   CAUTION: Do not connect the test fixture ground strap to any heat sink in this receiver.

Electrostatically Sensitive (ES) Devices

Some semiconductor (solid-state) devices can be damaged easily by static electricity. Such components commonly are called *Electrostatically Sensitive (ES) Devices.* Examples of typical ES devices are integrated circuits and some field-effect transistors and semiconductor "chip" components. The following techniques should be used to help reduce the incidence of component damage caused by static by static electricity.

1. Immediately before handling any semiconductor component or semiconductor-equipped assembly, drain off any electrostatic charge on your body by touching a known earth ground. Alternatively, obtain and wear a commercially available discharging wrist strap device, which should be removed to prevent potential shock reasons prior to applying power to the unit under test.
2. After removing an electrical assembly equipped with ES devices, place the assembly on a conductive surface such as aluminum foil, to prevent electrostatic charge buildup or exposure of the assembly.
3. Use only a grounded-tip soldering iron to solder or unsolder ES devices.
4. Use only an anti-static type solder removal device. Some solder removal devices not classified as "anti-static" can generate electrical charges sufficient to damage ES devices.
5. Do not use freon-propelled chemicals. These can generate electrical charges sufficient to damage ES devices.
6. Do not remove a replacement ES device from its protective package until immediately before you are ready to install it. (Most replacement ES devices are packaged with leads electrically shorted together by conductive foam, aluminum foil or comparable conductive material).
7. Immediately before removing the protective material from the leads of a replacement ES device, touch the protective material to the chassis or circuit assembly into which the device will be installed.
   CAUTION: Be sure no power is applied to the chassis or circuit, and observe all other safety precautions.
8. Minimize bodily motions when handling unpackaged replacement ES devices. (Otherwise harmless motion such as the brushing together of your clothes fabric or the lifting of your foot from a carpeted floor can generate static electricity sufficient to damage an ES device.)

General Soldering Guidelines

1. Use a grounded-tip, low-wattage soldering iron and appropriate tip size and shape that will maintain tip temperature within the range or 500°F to 600°F.
2. Use an appropriate gauge of RMA resin-core solder composed of 60 parts tin/40 parts lead.
3. Keep the soldering iron tip clean and well tinned.
4. Thoroughly clean the surfaces to be soldered. Use a mall wire-bristle (0.5 inch, or 1.25cm) brush with a metal handle.
   Do not use freon-propelled spray-on cleaners.
5. Use the following unsoldering technique
   a. Allow the soldering iron tip to reach normal temperature. (500°F to 600°F)
   b. Heat the component lead until the solder melts.
   c. Quickly draw the melted solder with an anti-static, suction-type solder removal device or with solder braid.
   CAUTION: Work quickly to avoid overheating the circuit board printed foil.
6. Use the following soldering technique.
   a. Allow the soldering iron tip to reach a normal temperature (500°F to 600°F)
   b. First, hold the soldering iron tip and solder the strand against the component lead until the solder melts.
   c. Quickly move the soldering iron tip to the junction of the component lead and the printed circuit foil, and hold it there only until the solder flows onto and around both the component lead and the foil.
   CAUTION: Work quickly to avoid overheating the circuit board printed foil.
   d. Closely inspect the solder area and remove any excess or splashed solder with a small wire-bristle brush.

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

IC Remove/Replacement

Some chassis circuit boards have slotted holes (oblong) through which the IC leads are inserted and then bent flat against the circuit foil. When holes are the slotted type, the following technique should be used to remove and replace the IC. When working with boards using the familiar round hole, use the standard technique as outlined in paragraphs 5 and 6 above.

Removal

1. Desolder and straighten each IC lead in one operation by gently prying up on the lead with the soldering iron tip as the solder melts.
2. Draw away the melted solder with an anti-static suction-type solder removal device (or with solder braid) before removing the IC.

Replacement

1. Carefully insert the replacement IC in the circuit board.
2. Carefully bend each IC lead against the circuit foil pad and solder it.
3. Clean the soldered areas with a small wire-bristle brush. (It is not necessary to reapply acrylic coating to the areas).

"Small-Signal" Discrete Transistor Removal/Replacement

1. Remove the defective transistor by clipping its leads as close as possible to the component body.
2. Bend into a "U" shape the end of each of three leads remaining on the circuit board.
3. Bend into a "U" shape the replacement transistor leads.
4. Connect the replacement transistor leads to the corresponding leads extending from the circuit board and crimp the "U" with long nose pliers to insure metal to metal contact then solder each connection.

Power Output, Transistor Device Removal/Replacement

1. Heat and remove all solder from around the transistor leads.
2. Remove the heat sink mounting screw (if so equipped).
3. Carefully remove the transistor from the heat sink of the circuit board.
4. Insert new transistor in the circuit board.
5. Solder each transistor lead, and clip off excess lead.
6. Replace heat sink.

Diode Removal/Replacement

1. Remove defective diode by clipping its leads as close as possible to diode body.
2. Bend the two remaining leads perpendicular y to the circuit board.
3. Observing diode polarity, wrap each lead of the new diode around the corresponding lead on the circuit board.
4. Securely crimp each connection and solder it.
5. Inspect (on the circuit board copper side) the solder joints of the two "original" leads. If they are not shiny, reheat them and if necessary, apply additional solder.

Fuse and Conventional Resistor Removal/Replacement

1. Clip each fuse or resistor lead at top of the circuit board hollow stake.
2. Securely crimp the leads of replacement component around notch at stake top.
3. Solder the connections.
   CAUTION: Maintain original spacing between the replaced component and adjacent components and the circuit board to prevent excessive component temperatures.

Circuit Board Foil Repair

Excessive heat applied to the copper foil of any printed circuit board will weaken the adhesive that bonds the foil to the circuit board causing the foil to separate from or "lift-off" the board. The following guidelines and procedures should be followed whenever this condition is encountered.

At IC Connections

To repair a defective copper pattern at IC connections use the following procedure to install a jumper wire on the copper pattern side of the circuit board. (Use this technique only on IC connections).

1. Carefully remove the damaged copper pattern with a sharp knife. (Remove only as much copper as absolutely necessary).
2. carefully scratch away the solder resist and acrylic coating (if used) from the end of the remaining copper pattern.
3. Bend a small "U" in one end of a small gauge jumper wire and carefully crimp it around the IC pin. Solder the IC connection.
4. Route the jumper wire along the path of the out-away copper pattern and let it overlap the previously scraped end of the good copper pattern. Solder the overlapped area and clip off any excess jumper wire.

At Other Connections

Use the following technique to repair the defective copper pattern at connections other than IC Pins. This technique involves the installation of a jumper wire on the component side of the circuit board.

1. Remove the defective copper pattern with a sharp knife. Remove at least 1/4 inch of copper, to ensure that a hazardous condition will not exist if the jumper wire opens.
2. Trace along the copper pattern from both sides of the pattern break and locate the nearest component that is directly connected to the affected copper pattern.
3. Connect insulated 20-gauge jumper wire from the lead of the nearest component on one side of the pattern break to the lead of the nearest component on the other side. Carefully crimp and solder the connections.
   CAUTION: Be sure the insulated jumper wire is dressed so the it does not touch components or sharp edges.

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

SPECIFICATION

NOTE : Specifications and others are subject to change without notice for improvement.

1. Application range

This spec sheet is applied LCD TV with LJ01U chassis.

2. Requirement for Test

Each part is tested as below without special appointment.

1) Temperature: 25 ºC ± 5 ºC
2) Relative Humidity: 65 ± 10 %
3) Power Voltage : Standard input voltage(100-240V~, 50/60Hz)
   * Standard Voltage of each product is marked by models
4) Specification and performance of each parts are followed each drawing and specification by part number in accordance with BOM.
5) The receiver must be operated for about 5 minutes prior to the adjustment.

3. Test method

1) Performance: LGE TV test method followed
2) Demanded other specification
   - Safety : UL, CSA, IEC specification
   - EMC: FCC, ICES, IEC specification

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

4. General Specification(TV)

No	Item	Specification			Remark
1	Receivable System	1) ATSC / NTSC-M			
2	Available Channel	1) VHF : 02 ~ 13 2) UHF : 14 ~ 69 3) DTV : 07 ~ 69 4) CATV : 01 ~ 135			
3	Input Voltage	1) AC 100 - 240V~ 50/60Hz			
4	Market	Central and South AMERICA			
5	Screen Size	26 inch Wide (1366 x 768)			26LK330
		32 inch Wide (1366 x 768)			32LV2500, 32LK330
		32 inch Wide (1920 x 1080)			32LV4500, 32LV3500, 32LV3400, 32LK450, 32LK430
		37 inch Wide (1920 x 1080)			37LV3500, 37LK450
		42 inch Wide (1920 x 1080)			42LV4500, 42LV3500, 42LV3400, 42LK550, 42LK450
		47 inch Wide (1920 x 1080)			47LV3500, 47LK450
		55 inch Wide (1920 x 1080)			55LV3500
6	Aspect Ratio	16:9			
7	Tuning System	FS			
8	LCD Module	T260XW04-V9	HD, 60Hz	AUO	26LK330
		T315XW03-VF	HD, 60Hz	AUO	32LK330
		LC320WXN-SCA2		LGD	
		LC320WXE-SCA1		LGD	
		T315HW04-V9	FHD, 60Hz	AUO	32LK430
		T315HW04-V9	FHD, 60Hz	AUO	32LK450
		LC320WUN-SDA1		LGD	
		LC320WUE-BCA1		LGD	
		T315XW06-V3	HD, 60Hz	AUO	32LV2500
		LC320EXN-SDA1		LGD	
		VVX32H110G00		IPS	
		LC320EUN-SDV2	FHD, 60Hz	LGD	32LV3400
		V315H3-LE7	FHD, 60Hz	CMI	32LV3500
		T315HW07-V8		AUO	
		LC320EUN-SDV2		LGD	
		LC320EUD-SDA1	FHD, 120Hz	LGD	32LV4500
		LC370WUE-SCA1	FHD, 60Hz	LGD	37LK450
		T370HW05-V1	FHD, 60Hz	LGD	37LV3500
		LC370EUN-SDV2		AUO	
		T420HW09-V0	FHD, 60Hz	AUO	42LK450
		LC420WUE-SCA2		LGD	
		LC420WUF-SCA2	FHD, 120Hz	LGD	42LK550
		LC420EUN-SDV3	FHD, 60Hz	LGD	42LV3400, 42LV3500
		T420HW08-V1	FHD, 60Hz	AUO	42LV3500
		LC420EUF-SDA1	FHD, 120Hz	LGD	42LV4500
		LC470WUE-SCA2	FHD, 60Hz	LGD	42LK450
		LC470EUE-SDV1	FHD, 60Hz	LGD	47LV3500
		LC550EUF-SDA1	FHD, 120Hz	LGD	55LV3500
9	Operating Environment	Temp : 0 ~ 40 deg Humidity : ~ 80 %			
10	Storage Environment	Temp : -20 ~ 60 deg Humidity : -85 %			

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

5. Chrominance & Luminance(32LV2500-SA)

No	Item			Min	Typ	Max	Unit	Remark
1	Max Luminance (Center 1-point / Full White Pattern)		Module	300	380		cd/m²	LGD
				280	350		cd/m²	AUO
				250	350		cd/m²	IPS
			SET	260	340		cd/m²	LGD
				240	310		cd/m²	AUO
				220	310		cd/m²	IPS
2	Luminance uniformity							
3	Color coordinate	RED	X	Typ. -0.03	0.637	Typ. +0.03		LGD
					0.640			AUO
					0.645			IPS
			Y		0.341			LGD
					0.330			AUO
					0.330			IPS
		GREEN	X		0.318			LGD
					0.310			AUO
					0.300			IPS
			Y		0.606			LGD
					0.620			AUO
					0.620			IPS
		BLUE	X		0.153			LGD
					0.150			AUO
					0.153			IPS
			Y		0.057			LGD
					0.060			AUO
					0.065			IPS
		WHITE	X		0.279			LGD
					0.280			AUO
					0.278			IPS
			Y		0.292			LGD
					0.290			AUO
					0.285			IPS
3.	Contrast ratio			850	1200			LGD
				2400	3000			AUO
				700	1200			IPS
4.	Color Temperature	Cool		0.254	0.269	0.284		<Test Condition>
				0.258	0.273	0.288		* The W/B Tolerance is ± 0.015 for Adjustment
		Standard		0.270	0.285	0.300		
				0.278	0.293	0.308		
		Warm		0.298	0.313	0.324		
				0.314	0.329	0.344		

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

6. Component Video Input (Y, C_B/P_B, C_R/P_R)

No	Resolution	H-freq(kHz)	V-freq.(kHz)	Pixel clock	Proposed
1.	720*576	15.625	50.000	13.5	SDTV 576I
2.	720*480	15.73	60	13.5135	SDTV ,DVD 480I
3.	720*480	15.73	59.94	13.5	SDTV ,DVD 480I
4.	720*480	31.50	60	27.027	SDTV 480P
5.	720*480	31.47	59.94	27.0	SDTV 480P
6.	720*576	31.250	50.000	27.000	SDTV 576P
7.	1280*720	37.500	50.000	74.25	HDTV 720P
8.	1280*720	45.00	60.00	74.25	HDTV 720P
9.	1280*720	44.96	59.94	74.176	HDTV 720P
10.	1920*1080	28.125	50.00	74.250	HDTV 1080I
11.	1920*1080	33.75	60.00	74.25	HDTV 1080I
12.	1920*1080	33.72	59.94	74.176	HDTV 1080I
13.	1920*1080	56.250	50.00	148.50	HDTV 1080P
14.	1920*1080	67.500	60	148.50	HDTV 1080P
15.	1920*1080	67.432	59.94	148.352	HDTV 1080P
16.	1920*1080	27.000	24.000	74.25	HDTV 1080P
17.	1920*1080	26.97	23.976	74.176	HDTV 1080P
18.	1920*1080	33.75	30.000	74.25	HDTV 1080P
19.	1920*1080	33.71	29.97	740176	HDTV 1080P

7. RGB Input (PC)

No	Resolution	H-freq(kHz)	V-freq.(kHz)	Pixel clock		Proposed	
	PC					DDC	
1.	640*350	31.468	70.09	25.17		EGA	X
2.	720*400	31.469	70.08	28.32		DOS	O
3.	640*480	31.469	59.94	25.17		VESA(VGA)	O
4.	800*600	37.879	60.31	40.00		VESA(SVGA)	O
5.	1024*768	48.363	60.00	65.00		VESA(XGA)	O
6.	1280*768	47.78	59.870	79.5		CVT(WXGA)	O
7.	1360*768	47.712	60.015	85.50		VESA(WXGA)	O
8.	1280*1024	63.981	60.020	108.00		VESA(SXGA)	O
9.	1920*1080	67.5	60	148.5		HDTV 1080P	O

•RGB PC Monitor Range Limits
Min Vertical Freq - 58 Hz
Max Vertical Freq - 62 Hz
Min Horiz. Freq - 30 kHz
Max Horiz. Freq - 83 kHz
Pixel Clock - 160 MHz

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

8. HDMI input (PC/DTV)

No	Resolution	H-freq(kHz)	V-freq.(kHz)	Pixel clock		Proposed	
	PC					DDC	
1.	640*350	31.468	70.09	25.17		EGA	X
2.	720*400	31.469	70.08	28.32		DOS	O
3.	640*480	31.469	59.94	25.17		VESA(VGA)	O
4.	800*600	37.879	60.31	40.00		VESA(SVGA)	O
5.	1024*768	48.363	60.00	65.00		VESA(XGA)	O
6.	1360*768	47.712	60.015	85.50		VESA (WXGA)	O
7.	1280*1024	63.981	60.020	108.00		VESA (SXGA)	O
8.	1920*1080	67.500	60.000	148.50		HDTV 1080P	O
	DTV						
1	720*480	31.469	59.940	27.000		SDTV 480P	
2	720*480	31.500	60	27.027		SDTV 480P	
3	720*576	31.250	50.000	27.000		SDTV 576P	
4	1280*720	37.500	50.000	74.25		HDTV 720P	
5	1280*720	45.00	60.00	74.25		HDTV 720P	
6	1280*720	44.96	59.94	74.176		HDTV 720P	
7	1920*1080	28.125	50.000	74.25		HDTV 1080I	
8	1920*1080	33.75	60.00	74.25		HDTV 1080I	
9	1920*1080	33.72	59.94	74.176		HDTV 1080I	
10	1920*1080	56.250	50.000	148.50		HDTV 1080P	
11	1920*1080	67.500	60	148.50		HDTV 1080P	
12	1920*1080	67.432	59.94	148.352		HDTV 1080P	
13	1920*1080	27.000	24.000	74.25		HDTV 1080P	
14	1920*1080	26.97	23.976	74.176		HDTV 1080P	
15	1920*1080	33.75	30.000	74.25		HDTV 1080P	
16	1920*1080	33.71	29.97	74.176		HDTV 1080P	

•HDMI Monitor Range Limits
Min Vertical Freq - 58 Hz Max Vertical Freq - 62 Hz
Min Horiz. Freq - 30 kHz Max Horiz. Freq - 83 kHz
Pixel Clock - 160 MHz

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

ADJUSTMENT INSTRUCTION

1. Application Range

This specification sheet is applied to all of the LCD TV with LJ01U/LJ01T/LJ01S chassis.

2. Designation

1) The adjustment is according to the order which is designated and which must be followed, according to the plan which can be changed only on agreeing.
2) Power Adjustment: Free Voltage
3) Magnetic Field Condition: Nil.
4) Input signal Unit: Product Specification Standard
5) Reserve after operation: Above 5 Minutes (Heat Run)
   Temperature : at 25 ºC ± 5 ºC
   Relative humidity : 65 % ± 10 %
   Input voltage : 100 ~ 220 V~, 50/60 Hz
6) Adjustment equipments: Color Analyzer(CA-210 or CA-110), DDC Adjustment Jig equipment, Service remote control.
7) Push the “IN STOP” key - For memory initialization.

Case1 : Software version up
1. After downloading S/W by USB, TV set will reboot automatically
2. Push “In-stop” key
3. Push “Power on” key
4. Function inspection
5. After function inspection, Push “In-stop” key.

Case2 : Function check at the assembly line
1. When TV set is entering on the assembly line, Push “In-stop” key at first.
2. Push “Power on” key for turning it on.
   -> If you push “Power on” key, TV set will recover channel information by itself.
3. After function inspection, Push “In-stop” key.

3. Main PCB check process

* APC - After Manual-Insult, executing APC

* Boot file Download

1) Execute ISP program “Mstar ISP Utility” and then click “Config” tab.



2) Set as below, and then click “Auto Detect” and check “OK” message
   If “Error” is displayed, Check connection between computer, jig, and set.
3) Click “Read” tab, and then load download file (XXXX.bin) by clicking “Read”
4) Click “Connect” tab. If “Can’t” is displayed, check connection between computer, jig, and set.



5) Click “Auto” tab and set as below
6) Click “Run”.
7) After downloading, check “OK” message.



* USB DOWNLOAD

1) Put the USB Stick to the USB socket
2) Automatically detecting update file in USB Stick
   - If your downloaded program version in USB Stick is Low, it didn’t work. But your downloaded version is High, USB data is automatically detecting
3) Show the message “Copying files from memory”



4) Updating is staring.



Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

5) Uploading completed, The TV will restart automatically.
6) If your TV is turned on, check your updated version and Tool option.(explain the Tool option, next stage)
   * If downloading version is more high than your TV have, TV can lost all channel data. In this case, you have to channel recover. if all channel data is cleared, you didn't have a DTV/ATV test on production line.

*** After downloading, have to adjust Tool Option again.**

1) Push "IN-START" key in service remote control.
2) Select “Tool Option 1” and Push “OK” button.
3) Punch in the number. (Each model has their number)
4) Completed selecting Tool option.

Module	Module	Tool option1	Tool option2	Tool option3	Tool option4	Tool option5
42LV4500-SA	LGD	26496	19478	55337	10520	8448
32LV4500-SA	LGD	18304	19478	55337	10520	8480
55LV3500-SA	LGD	46944	19478	55337	10520	8448
47LV3500-SA	LGD	34656	19478	55337	10520	256
42LV3500-SA	AUO	26472	19478	55337	10520	352
42LV3500-SA	LGD	26464	19478	55337	10520	288
37LV3500-SA	AUO	22376	19478	55337	10520	352
37LV3500-SA	LGD	22368	19478	55337	10520	288
32LV3500-SA	CMI	18276	19478	55337	10520	352
32LV3500-SA	AUO	18280	19478	55337	10520	352
32LV3500-SA	LGD	18272	19478	55337	10520	288
42LV3400-SA	LGD	26592	9226	53289	10520	288
32LV3400-SA	LGD	18400	9226	53289	10520	288
32LV2500-SA	CMI	18212	19478	55337	10520	352
32LV2500-SA	AUO	18216	19478	55337	10520	352
32LV2500-SA	LGD	18208	19478	55337	10520	288
26LV2500-SA	AUO	14120	8714	55337	10520	288
26LV2500-SA	LGD	14112	8714	55337	10520	288
22LV2500-SA	CMI	10020	8714	55337	10520	288
22LV2500-SA	AUO	10024	8714	55337	10520	288
19LV2500-SA	AUO	5928	8714	55337	10520	288
19LV2500-SA	CMI	5924	8714	55337	10520	288
19LV2500-SA	LGD	5920	8714	55337	10520	288
47LK450-SA	LGD	34432	18966	55305	10520	8450
42LK450-SA	LGD	26240	18966	55305	10520	8450
42LK450-SA	AUO	26248	18966	55305	10520	290
37LK450-SA	LGD	22144	18966	55305	10520	8450
37LK450-SA	AUO	22152	18966	55305	10520	290
32LK450-SA	AUO	18056	18966	55305	10520	290
32LK450-SA	LGD	18048	18966	55305	10520	8482
32LK450-SA	LGD (CoMS)	18048	18966	55305	10520	8450
32LK430-SA	AUO	18024	18966	51209	10520	290
32LK330-SB	AUO	17992	18966	51209	10520	290
32LK330-SB	LGD	17984	18966	51209	10520	290
32LK330-SB	LGD (CoMS)	17984	18966	51209	10520	258
26LK330-SB	AUO	13896	18966	51209	10520	290

3.1. ADC Process

(1) ADC
- Enter Service Mode by pushing “ADJ” key,
- Enter Internal ADC mode by pushing “$_G$” key at “6. ADC Calibration”





<Caution> Using ‘power on’ button of the Adjustment R/C, power on TV.

* ADC Calibration Protocol (RS232)

No	Item	CMD1	CMD2	Data0		
Enter Adjust Mode	Adjust ‘Mode In’	A	A	0	0	When transfer the ‘Mode In’, Carry the command.
ADC adjust	ADC Adjust	A	D	1	0	Automatically adjustment (The use of a internal pattern)

Adjust Sequence
- aa 00 00 [Enter Adjust Mode]
- xb 00 40 [Component1 Input (480i)]
- ad 00 10 [Adjust 480i Comp1]
- xb 00 60 [RGB Input (1024*768)]
- ad 00 10 [Adjust 1024*768 RGB]
- aa 00 90 End Adjust mode

* Required equipment : Adjustment R/C.

3.2. Function Check

* Check display and sound
- Check Input and Signal items. (cf. work instructions)
  1) TV
  2) AV (SCART1/SCART2/ CVBS)
  3) COMPONENT (480i)
  4) RGB (PC : 1024 x 768 @ 60hz)
  5) HDMI
  6) PC Audio In
  * Display and Sound check is executed by Remote control.

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

4. Total Assembly line process

4.1. Adjustment Preparation

· W/B Equipment condition
CA210 : CH 9, Test signal : Inner pattern (85IRE)
· Above 5 minutes H/run in the inner pattern. (“power on” key of adjust remote control)

Cool	13,000	K	X=0.269(±0.002)	
			Y=0.273(±0.002)	<Test Signal>
Medium	9,300	K	X=0.285(±0.002)	Inner pattern
			Y=0.293(±0.002)	(216gray,85IRE)
Warm	6,500	K	X=0.313(±0.002)	
			Y=0.329(±0.002)	

* Connecting picture of the measuring instrument
(On Automatic control)
Inside PATTERN is used when W/B is controlled. Connect to auto controller or push Adjustment R/C POWER ON -> Enter the mode of White-Balance, the pattern will come out.



* Auto-control interface and directions
1) Adjust in the place where the influx of light like floodlight around is blocked. (illumination is less than 10 lux).
2) Adhere closely the Color Analyzer (CA210) to the module less than 10 cm distance, keep it with the surface of the Module and Color Analyzer’s prove vertically.(80° ~ 100°).
3) Aging time
- After aging start, keep the power on (no suspension of power supply) and heat-run over 5 minutes.
- Using ‘no signal’ or ‘full white pattern’ or the others, check the back light on.

• Auto adjustment Map(RS-232C)
RS-232C COMMAND
[CMD ID DATA]
Wb 00 00 White Balance Start
Wb 00 ff White Balance End

	RS-232C COMMAND [CMD ID DATA]			MIN	CENTER (DEFAULT)			MAX
	Cool	Mid	Warm		Cool	Mid	Warm	
R Gain	jg	Ja	jd	00	172	192	192	192
G Gain	jh	Jb	je	00	172	192	192	192
B Gain	ji	Jc	jf	00	192	192	172	192
R Cut					64	64	64	128
G Cut					64	64	64	128
B Cut					64	64	64	128

<Caution>
Color Temperature : COOL, Medium, Warm.
One of R Gain/G Gain/ B Gain should be kept on 0xC0, and adjust other two lower than C0.
(when R/G/B Gain are all C0, it is the FULL Dynamic Range of Module)

* Manual W/B process using adjusts Remote control.
• After enter Service Mode by pushing “ADJ” key,
• Enter White Balance by pushing “G” key at “6. White Balance”.





* After done all adjustments, Press “In-start” button and compare Tool option and Area option value with its BOM, if it is correctly same then unplug the AC cable. If it is not same, then correct it same with BOM and unplug AC cable. For correct it to the model’s module from factory Jig model.
* Push the “IN STOP” key after completing the function inspection. And Mechanical Power Switch must be set “ON”.

4.2. DDC EDID Write (RGB 128Byte)

• Connect D-sub Signal Cable to D-sub Jack.
• Write EDID Data to EEPROM(24C02) by using DDC2B protocol.
• Check whether written EDID data is correct or not.
* For SVC main Assembly, EDID have to be downloaded to Insert Process in advance.

4.3. DDC EDID Write (HDMI 256Byte)

• Connect HDMI Signal Cable to HDMI Jack.
• Write EDID Data to EEPROM(24C02) by using DDC2B protocol.
• Check whether written EDID data is correct or not.
* For SVC main Assembly, EDID have to be downloaded to Insert Process in advance.

4.4. EDID DATA

1) All Data : HEXA Value
2) Changeable Data :
*: Serial No : Controlled / Data:01
**: Month : Controlled / Data:00
***:Year : Controlled
****:Check sum

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

4.5. Auto Download

1) Press Adj. key on the Adj. Remote control.
2) Select EDID D/L menu.
3) By pressing Enter key, EDID download will begin
4) If Download is successful, OK is display, but If Download if failure, NG is displayed.
5) If Download is failure, Re-try downloads.



* Edid data and Model option download (RS232)

NO	Item	CMD1	CMD2	Data0		
Enter download Mode	Download 'Mode In'	A	A	0	0	When transfer the 'Mode In', Carry the command.
EDID data and Model option download	Download	A	E	00	10	Automatically Download (The use of a internal pattern)

- Manual Download

* Caution
1) Use the proper signal cable for EDID Download
   - Analog EDID : Pin3 exists
   - Digital EDID : Pin3 exists
2) Never connect HDMI & D-sub Cable at the same time.
3) Use the proper cables below for EDID Writing
4) Download HDMI1, HDMI2, separately because HDMI1 is different from HDMI2

For Analog EDID	For HDMI EDID
D-sub to D-sub	DVI-D to HDMI or HDMI to HDMI

Item	Condition	Data(Hex)
Manufacturer ID	GSM	1E6D
Version	Digital : 1	01
Revision	Digital : 3	03

1) FHD RGB EDID data(Check sum:1C)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	68	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	81	80	61	40	45	40	31	40	01	01
0030	01	01	01	01	01	02	3A	80	18	71	38	2D	40	58	2C	
0040	45	00	A0	5A	00	00	00	1E	01	1D	00	72	51	D0	1E	20
0050	6E	28	55	00	A0	5A	00	00	00	1E	00	00	00	FD	00	3A
0060	3E	1E	53	10	00	0A	20	20	20	20	20	20	20	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	00	1C

2) FHD HDMI EDID data
HDMI 1 (Check sum:E2, 99)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	80	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	71	4F	81	80	01	01	01	01	01	01
0030	01	01	01	01	01	01	02	3A	80	18	71	38	2D	40	58	2C
0040	45	00	A0	5A	00	00	00	1E	1B	21	50	A0	51	00	1E	30
0050	48	88	35	00	A0	5A	00	00	00	1C	00	00	00	FD	00	3A
0060	3E	1E	53	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	01	E2
0080	02	03	26	F1	4E	10	1F	04	13	05	14	03	02	12	20	21
0090	22	15	01	26	15	07	50	09	57	07	67	03	0C	00	10	00
00A0	B8	2D	E3	05	03	01	01	1D	80	18	71	1C	16	20	58	2C
00B0	25	00	A0	5A	00	00	00	9E	01	1D	00	72	51	D0	1E	20
00C0	6E	28	55	00	A0	5A	00	00	00	1E	02	3A	80	18	71	38
00D0	2D	40	58	2C	45	00	A0	5A	00	00	00	1E	01	1D	00	BC
00E0	52	D0	1E	20	B8	28	55	40	A0	5A	00	00	00	1E	00	00
00F0	00	00	00	00	00	00	00	00	00	00	00	00	00	00	00	99

HDMI 2 (Check sum:E2, 89)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	80	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	71	4F	81	80	01	01	01	01	01	01
0030	01	01	01	01	01	01	02	3A	80	18	71	38	2D	40	58	2C
0040	45	00	A0	5A	00	00	00	1E	1B	21	50	A0	51	00	1E	30
0050	48	88	35	00	A0	5A	00	00	00	1C	00	00	00	FD	00	3A
0060	3E	1E	53	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	01	E2
0080	02	03	26	F1	4E	10	1F	04	13	05	14	03	02	12	20	21
0090	22	15	01	26	15	07	50	09	57	07	67	03	0C	00	20	00
00A0	B8	2D	E3	05	03	01	01	1D	80	18	71	1C	16	20	58	2C
00B0	25	00	A0	5A	00	00	00	9E	01	1D	00	72	51	D0	1E	20
00C0	6E	28	55	00	A0	5A	00	00	00	1E	02	3A	80	18	71	38
00D0	2D	40	58	2C	45	00	A0	5A	00	00	00	1E	01	1D	00	BC
00E0	52	D0	1E	20	B8	28	55	40	A0	5A	00	00	00	1E	00	00
00F0	00	00	00	00	00	00	00	00	00	00	00	00	00	00	00	89

HDMI 3 (Check sum:E2, 79)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	80	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	71	4F	81	80	01	01	01	01	01	01
0030	01	01	01	01	01	01	02	3A	80	18	71	38	2D	40	58	2C
0040	45	00	A0	5A	00	00	00	1E	1B	21	50	A0	51	00	1E	30
0050	48	88	35	00	A0	5A	00	00	00	1C	00	00	00	FD	00	3A
0060	3E	1E	53	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	01	E2
0080	02	03	26	F1	4E	10	1F	04	13	05	14	03	02	12	20	21
0090	22	15	01	26	15	07	50	09	57	07	67	03	0C	00	30	00
00A0	B8	2D	E3	05	03	01	01	1D	80	18	71	1C	16	20	58	2C
00B0	25	00	A0	5A	00	00	00	9E	01	1D	00	72	51	D0	1E	20
00C0	6E	28	55	00	A0	5A	00	00	00	1E	02	3A	80	18	71	38
00D0	2D	40	58	2C	45	00	A0	5A	00	00	00	1E	01	1D	00	BC
00E0	52	D0	1E	20	B8	28	55	40	A0	5A	00	00	00	1E	00	00
00F0	00	00	00	00	00	00	00	00	00	00	00	00	00	00	00	79

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

3) HD RGB EDID data(Check sum:CD)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	68	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	81	C0	61	40	45	40	31	40	01	01
0030	01	01	01	01	01	01	1B	21	50	A0	51	00	1E	30	48	88
0040	35	00	A0	5A	00	00	00	1C	01	1D	00	72	51	D0	1E	20
0050	6E	28	55	00	A0	5A	00	00	00	1E	00	00	00	FD	00	3A
0060	3E	1F	46	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	00	CD
0080	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
0090	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
00A0	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
00B0	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
00C0	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
00D0	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
00E0	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF
00F0	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF	FF

4) HD HDMI EDID data
HDMI 1 (Check sum:B4, 65)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	80	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	81	C0	61	40	45	40	31	40	01	01
0030	01	01	01	01	01	01	1B	21	50	A0	51	00	1E	30	48	88
0040	35	00	A0	5A	00	00	00	1C	01	1D	00	72	51	D0	1E	20
0050	6E	28	55	00	A0	5A	00	00	00	1E	00	00	00	FD	00	3A
0060	3E	1F	46	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	01	B4
0080	02	03	20	F1	4E	10	1F	84	13	05	14	03	02	12	20	21
0090	22	15	01	26	15	07	50	09	57	07	65	03	0C	00	10	00
00A0	01	1D	80	18	71	1C	16	20	58	2C	25	00	A0	5A	00	00
00B0	00	9E	01	1D	00	80	51	D0	0C	20	40	80	35	00	A0	5A
00C0	00	00	00	1E	8C	0A	D0	8A	20	E0	2D	10	10	3E	96	00
00D0	A0	5A	00	00	00	18	02	3A	80	18	71	38	2D	40	58	2C
00E0	45	00	A0	5A	00	00	00	1E	01	1D	80	D0	72	1C	16	20
00F0	10	2C	25	80	A0	5A	00	00	00	9E	00	00	00	00	00	65

HDMI 2 (Check sum:B4, 55)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	80	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	81	C0	61	40	45	40	31	40	01	01
0030	01	01	01	01	01	01	1B	21	50	A0	51	00	1E	30	48	88
0040	35	00	A0	5A	00	00	00	1C	01	1D	00	72	51	D0	1E	20
0050	6E	28	55	00	A0	5A	00	00	00	1E	00	00	00	FD	00	3A
0060	3E	1F	46	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	01	B4
0080	02	03	20	F1	4E	10	1F	84	13	05	14	03	02	12	20	21
0090	22	15	01	26	15	07	50	09	57	07	65	03	0C	00	20	00
00A0	01	1D	80	18	71	1C	16	20	58	2C	25	00	A0	5A	00	00
00B0	00	9E	01	1D	00	80	51	D0	0C	20	40	80	35	00	A0	5A
00C0	00	00	00	1E	8C	0A	D0	8A	20	E0	2D	10	10	3E	96	00
00D0	A0	5A	00	00	00	18	02	3A	80	18	71	38	2D	40	58	2C
00E0	45	00	A0	5A	00	00	00	1E	01	1D	80	D0	72	1C	16	20
00F0	10	2C	25	80	A0	5A	00	00	00	9E	00	00	00	00	00	55

HDMI 3 (Check sum:B4, 45)

Addr	00	01	02	03	04	05	06	07	08	09	0A	0B	0C	0D	0E	0F
0000	00	FF	FF	FF	FF	FF	FF	00	1E	6D	01	00	01	01	01	01
0010	01	15	01	03	80	10	09	78	0A	EE	91	A3	54	4C	99	26
0020	0F	50	54	A1	08	00	81	C0	61	40	45	40	31	40	01	01
0030	01	01	01	01	01	01	1B	21	50	A0	51	00	1E	30	48	88
0040	35	00	A0	5A	00	00	00	1C	01	1D	00	72	51	D0	1E	20
0050	6E	28	55	00	A0	5A	00	00	00	1E	00	00	00	FD	00	3A
0060	3E	1F	46	10	00	0A	20	20	20	20	20	20	00	00	00	FC
0070	00	4C	47	20	54	56	0A	20	20	20	20	20	20	20	01	B4
0080	02	03	20	F1	4E	10	1F	84	13	05	14	03	02	12	20	21
0090	22	15	01	26	15	07	50	09	57	07	65	03	0C	00	30	00
00A0	01	1D	80	18	71	1C	16	20	58	2C	25	00	A0	5A	00	00
00B0	00	9E	01	1D	00	80	51	D0	0C	20	40	80	35	00	A0	5A
00C0	00	00	00	1E	8C	0A	D0	8A	20	E0	2D	10	10	3E	96	00
00D0	A0	5A	00	00	00	18	02	3A	80	18	71	38	2D	40	58	2C
00E0	45	00	A0	5A	00	00	00	1E	01	1D	80	D0	72	1C	16	20
00F0	10	2C	25	80	A0	5A	00	00	00	9E	00	00	00	00	00	45

- Model List

HD(CCFL)	FHD(CCFL)	HD(LED)	FHD Small(LED)	FHD(LED)
32LK330-SB	32LK450-SA	19LV2500-SA		32LV4500-SA
	37LK450-SA	22LV2500-SA		42LV4500-SA
	42LK450-SA	26LV2500-SA		32LV3500-SA
	47LK450-SA	32LV2500-SA		37LV3500-SA
	32LK430-SA			42LV3500-SA
				47LV3500-SA
				55LV3500-SA

4.5. Outgoing condition Configuration

- When pressing IN-STOP key by SVC remocon, Red LED are blinked alternatively. And then Automatically turn off. (Must not AC power OFF during blinking)

4.6. Hi-pot Test

Confirm whether is normal or not when between power board's ac block and GND is impacted on 1.5 kV/min at 100mA(GND) and 3kV/min at 100mA(Signal)

Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

EXPLODED VIEW

IMPORTANT SAFETY NOTICE

Many electrical and mechanical parts in this chassis have special safety-related characteristics. These parts are identified by ⚠ in the Schematic Diagram and EXPLODED VIEW.
It is essential that these special safety parts should be replaced with the same components as recommended in this manual to prevent X-RADIATION, Shock, Fire, or other Hazards.
Do not modify the original design without permission of manufacturer.



Copyright © 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

S7M-PLUS_DivX_MS10

LGE107DC-RP [S7M+ DIVX/MS10]

NAND FLASH MEMORY

IC102
NAND01GW3B2CN6E

NAND_FLASH_1G_NUMONYX
EAN60762401

+3.3V_Normal

/PF_CE0
H : Serial Flash
L : NAND Flash
/PF_CE1
H : 16 bit
L : 8 bit

/F_RB
/PF_OE
/PF_CE0
/PF_WP
/PF_CE1
PF_ALE
/PF_WE

R107 1K
R109 3.9K
R108 1K OPT
R105 1K OPT
R104 10K OPT
R106
R102 3.3K
C101 0.1uF
C102 10uF
C103 0.1uF
Q101 KRC103S OPT

AR101 22
AR102 22

PCM_A[0-7]
PCM_A[7]
PCM_A[6]
PCM_A[5]
PCM_A[4]
PCM_A[3]
PCM_A[2]
PCM_A[1]
PCM_A[0]

<T3 CHIP Config(AUD_LRCH)>

Boot from SPI flash : 1'b0
Boot from NOR flash : 1'b1

<T3 CHIP Config>
(AUD_SCK, AUD_MASTER_CLK, PWM1, PWM0)

MIPS_no_EJ_NOR8 : 4'h3 (MIPS as host. No EJ PAD. Byte mode NAND flash.)
MIPS_EJ1_NOR8 : 4'h4 (MIPS as host. EJ use PAD1. Byte mode NAND flash)
MIPS_EJ2_NOR8 : 4'h5 (MIPS as host. EJ use PAD2. Byte mode NAND flash.)
B51_Secure_no scramble : 4'hb (8051 as host. Internal SPI flash secure boot, no scramble)
B51_Sesure_scramble : 4'hc (8051 as host. Internal SPI flash secure boot with scarmble)

+3.3V_Normal
AUD_MASTER_CLK
R148 56
C112 100pF 50V
R115 1K
R123 1K OPT
R125 1K OPT
R116 1K
R118 1K OPT
R121 1K OPT
R124 1K
R126 1K
AUD_LRCH
AUD_SCK
AUD_MASTER_CLK_0
PWM1
PWM0

IC101

PCM_D[0-7]
PCM_A[0-14]
PCM_REG
PCM_OE
PCM_WE
PCM_IORD
PCM_IOWR
PCM_CE
PCM_IRQA
PCM_CD
PCM_WAIT
PCM_RST
/PF_CE0
/PF_CE1
/PF_OE
/PF_WE
PF_ALE
/PF_WP
/F_RB
S7_NEC_TXD
S7_NEC_RXD
I2C_SDA
I2C_SCL
RGB_DDC_SDA
RGB_DDC_SCL
PWM0
PWM1
PWM2
SC_RE2
SC_RE1
DSUB_DET
MODEL_OPT_3
PCM_5V_CTL
/RST-PHY

+5V_Normal
R132 10K
R133 10K
C108 0.1uF OPT
C109 0.1uF
AR104 22
AR103 22
R134 22
R135 22
R136 22
R137 22
R138 22
R139 22

for SYSTEM/HDCP EEPROM&URSA3
TO SCART1

PCM_D0 U22
PCM_D1 T21
PCM_D2 T22
PCM_D3 AB18
PCM_D4 AC18
PCM_D5 AC19
PCM_D6 AC20
PCM_D7 AC21
PCM_A0 U21
PCM_A1 V21
PCM_A2 Y22
PCM_A3 AA22
PCM_A4 R22
PCM_A5 R21
PCM_A6 T23
PCM_A7 T24
PCM_A8 AA23
PCM_A9 Y20
PCM_A10 AB17
PCM_A11 AA21
PCM_A12 U23
PCM_A13 Y23
PCM_A14 W23
W22
PCM_REG_N
AA17
PCM_OE_N V22
PCM_WE_N W21
PCM_IORD_N Y21
PCM_IOWR_N
AA20
PCM_CE_N V23
PCM_IRQA_N P23
PCM_CD_N R23
PCM_WAIT_N P22
PCM_RESET
AC17
PCM_PF_CE0Z AB20
PCM_PF_CE1Z AA18
PCM_PF_OEZ AB21
PCM_PF_WEZ AB19
PCM_PF_ALE AD17
PCM_PF_AD[15] AA19
PCM_PF_RBZ
M23
UART_TX2/GPIO65 N23
UART_RX2/GPIO64
DDCR_DA/GPIO71 M22
DDCR_CK/GPIO72 N22
DDCA_DA/UART0_TX A5
DDCA_CK/UART0_RX B5
K23
PWM0/GPIO66 K22
PWM1/GPIO67 G23
PWM2/GPIO68 G22
PWM3/GPIO69 G21
PWM4/GPIO70
C6
SAR0/GPIO31 B6
SAR1/GPIO32 C8
SAR2/GPIO33 C7
SAR3/GPIO34 A6
SAR4/GPIO35

GPIO143/TCON0 N21
GPIO145/TCON2 M21
GPIO147/TCON4 L22
GPIO149/TCON6 L21
GPIO151/TCON8 P21
5V_DET_HDMI_1
5V_DET_HDMI_2
5V_DET_HDMI_4
SIDEAV_DET

Delete Wireless

GPIO36/UART3_RX K21
GPIO37/UART3_TX L23
GPIO38 K20
GPIO39 L20
GPIO40 M20
GPIO41 G20
GPIO42 G19
ET_RXER
FRC_RESET
SC1/COMP1_DET
ERROR_OUT
MODEL_OPT_0

GPIO50/UART1_RX F20
GPIO51/UART1_TX F19

GPIO6/PM0/INT0 E7
GPIO7/PM1/PM_UART_TX D7
GPIO8/PM2 E11
GPIO9/PM3 G9
GPIO10/PM4 F9
GPIO11/PM5/PM_UART_RX/INT1 C5
USB1_OCD
USB1_CTL
HP_DET
CONTROL_ATTEN
MODEL_OPT_6
MODEL_OPT_1

PM_SPI_CS1/GPIO12/PM6 E8 33 R146
PM_SPI_WP1/GPIO13/PM7 E9
PM_SPI_WP2/GPIO14/PM8/INT2 F7
GPIO15/PM9 F6
PM_SPI_CS2/GPIO16/PM10 D8
GPIO17/PM11/INT3 G12
GPIO18/PM12/INT4 F10
/FLASH_WP
MODEL_OPT_2
TUNER_RESET
DEMOD_RESET
AV_CVBS_DET

PM_SPI_CK/GPIO1 D9 33 R147
PM_SPI_CZ/GPIO0 D11
PM_SPI_DI/GPIO2 E10
PM_SPI_DO/GPIO3 D10 33 R151
SPI_SCK
/SPI_CS
SPI_SDI
SPI_SDO
for SERIAL FLASH

TS0_CLK AA9
TS0_VLD AA5
TS0_SYNC AA10
CI_TS_CLK
CI_TS_VAL
CI_TS_SYNC
CI_TS_DATA[0-7]
from CI SLOT

TS0_D0 AB5 CI_TS_DATA[0]
TS0_D1 AC4 CI_TS_DATA[1]
TS0_D2 Y6 CI_TS_DATA[2]
TS0_D3 AA6 CI_TS_DATA[3]
TS0_D4 W6 CI_TS_DATA[4]
TS0_D5 AA7 CI_TS_DATA[5]
TS0_D6 Y9 CI_TS_DATA[6]
TS0_D7 AA8 CI_TS_DATA[7]

TS1_CLK AC5
TS1_VLD AC6
TS1_SYNC AB6
FE_TS_CLK
FE_TS_VAL_ERR
FE_TS_SYNC
FE_TS_DATA[7-0]
Internal demod out /External demod in

TS1_D0 AC10 FE_TS_DATA[0]
TS1_D1 AB10 FE_TS_DATA[1]
TS1_D2 AC9 FE_TS_DATA[2]
TS1_D3 AB9 FE_TS_DATA[3]
TS1_D4 AC8 FE_TS_DATA[4]
TS1_D5 AB8 FE_TS_DATA[5]
TS1_D6 AC7 FE_TS_DATA[6]
TS1_D7 AB7 FE_TS_DATA[7]

MPIF_CLK D12
MPIF_CS_N D14
MPIF_BUSY E14
R160 1K
Delete /PIF_SPI_CS

MPIF_D0 E12
MPIF_D1 F12
MPIF_D2 D13
MPIF_D3 E13

NAND_FLASH_1G_HYNIX
EAN35669102
IC102-*1
H27U1G8F2BTR-BC

NAND_FLASH_1G_SS
EAN61857001
IC102-*2
K9F1G08U0D-SCB0

NAND_FLASH_1G_TOSHIBA
EAN61508001
IC102-*3
TC58NVG0S3ETA0BBBH

S7R

S7R_BASIC | S7R_MS10 | S7R_DivX | S7R_DivX_MS10 | S7R_RM

S7MR

S7MR_BASIC | S7MR_MS10 | S7MR_DivX | S7MR_DivX_MS10 | S7MR_RM

S7MR-PLUS

S7M-PLUS_BASIC | S7M-PLUS_MS10 | S7M-PLUS_DivX | S7M-PLUS_RM

EEPROM_1MBIT_ATMEL
IC104-*1
AT24C1024BN-SH-T

NC A1 A2 GND VCC WP SCL SDA

HDCP EEPROM

IC103
CAT24WC08W-T
Addr:10101--
+3.3V_Normal
R113 4.7K
C107 0.1uF
R127 4.7K
R128 22
R129 22
I2C_SCL
I2C_SDA

EEPROM

EEPROM_1MBIT_ST
IC104
M24M01-HRMN6TP
A0'h
C105 0.1uF
C104 8pF OPT
C106 8pF OPT
R111 22
R112 22
I2C_SCL
I2C_SDA

I2C

+3.3V_Normal
R140
R141
R142 3.3K
R143 3.3K
R144
R145
AMP_SDA
AMP_SCL
I2C_SDA
I2C_SCL
NEC_SDA
NEC_SCL

DIMMING

A_DIM
PWM_DIM
SCAN_BLK2
SCAN_BLK1/OPC_OUT
R156 10K
R157 100
R155 0
C111 2.2uF OPT
R158 100 OPT
R159 100 OPT
PWM0
PWM2
FRC_PWM1
FRC_PWM0
LD650 Scan

FRC_SCL
FRC_SDA

THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET
LGElectronics

LG ELECTRONICS

MODEL	GP3_Saturn7M	DATE	Ver. 0.1
BLOCK	FLASH/EEPROM/GPIO	SHEET	1 /

MODEL OPTION

PIN NAME	PIN NO.	LOW	HIGH
MODEL_OPT_0	G19	NO FRC	FRC
MODEL_OPT_4	E18	50/60Hz LVDS	100/120Hz LVDS
MODEL_OPT_1	C5	PHM_OFF	PHM_ON
MODEL_OPT_2	F7	2D	3D
MODEL_OPT_3	B6	HD	FHD
MODEL_OPT_5	D18	Ready	default
MODEL_OPT_6	F9	LCD	OLED

NO_FRC : LOW LOW
U3_INTERNAL : HIGH LOW
U5_EXTERNALBOOT :HIGH HIGH
reserved for FRC : LOW HIGH

--> This option is only applied in EU.
In case of NON_EU, default value set LOW.

-->In case of GP2, This port was used for GIP/NON_GIP

RSDS Power OPT

VDDC 1.26V

Normal Power 3.3V

Normal 2.5V

DDR3 1.5V

RSDS Power OPT

S7M-PLUS_DivX_MS10
IC101
LGE107DC-RP [S7M+ DIVX/MS10]

HDMI

DSUB

SCART1_RGB/COMP1

COMP2

CVBS In/OUT

Close to MSTAR

DTV_IF

ANALOG SIF
Close to MSTAR

TU/DEMOD_I2C

B/T USB

SIDE USB

I2S_I/F

AUDIO IN

AUDIO OUT

H/P OUT

Delete CHB_CVBS_IN

THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET
LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	MAIN2, HW OPT	SHEET	2

DDR3 1.5V By CAP - Place these Caps near Memory

VCC1.5V_U3_DDR

C301 10uF

C303 0.1uF, C304 OPT, C305 0.1uF, C306 0.1uF, C307 0.1uF, C308 0.1uF, C309 0.1uF, C310 0.1uF, C311 0.1uF, C313 0.1uF, C315 0.1uF, C316 0.1uF, C317 0.1uF, C318 0.1uF, C319 0.1uF, C320 0.1uF, C321 0.1uF, C322 0.1uF, C323 0.1uF

Close to DDR Power Pin

+1.5V_FRC_DDR

L301

C324 10uF 10V

VCC1.5V_U3_DDR

C325 0.1uF 16V

VCC1.5V_U3_DDR

R301 1K 1%

R302 1K 1%

C302 0.1uF

C304 100pF

C-MVREFDQ

CLose to DDR3

VCC1.5V_U3_DDR

R304 1K 1%

R305 1K 1%

C312 0.1uF

C314 1000pF

C-MVREFCA

CLose to Saturn7M IC

EAN61828901

IC301

H5TQ1G63DFR-H9C

FRC_DDR_1333_HYNIX

C-MVREFCA → M8 VREFCA

C-MVREFDQ → H1 VREFDQ

R303 240 1% → L8 ZQ

VCC1.5V_U3_DDR

VDD_1 B2, VDD_2 D9, VDD_3 G7, VDD_4 K2, VDD_5 K8, VDD_6 N1, VDD_7 N9, VDD_8 R1, VDD_9 R9

VDDQ_1 A1, VDDQ_2 A8, VDDQ_3 C1, VDDQ_4 C9, VDDQ_5 D2, VDDQ_6 E9, VDDQ_7 F1, VDDQ_8 H2, VDD9 H9

NC_1 J1, NC_2 J9, NC_3 L1, NC_4 L9, NC_6 T7

VSS_1 A9, VSS_2 B3, VSS_3 E1, VSS_4 G8, VSS_5 J2, VSS_6 J8, VSS_7 M1, VSS_8 M9, VSS_9 P1, VSS_10 T1, VSS_11 T9, VSS_12

VSSQ_1 B1, VSSQ_2 B9, VSSQ_3 D1, VSSQ_4 D8, VSSQ_5 E2, VSSQ_6 E8, VSSQ_7 F9, VSSQ_8 G1, VSSQ_9 G9

A0 N3 C-MA0, A1 P7 C-MA1, A2 P3 C-MA2, A3 N2 C-MA3, A4 P8 C-MA4, A5 P2 C-MA5, A6 R8 C-MA6, A7 R2 C-MA7, A8 T8 C-MA8, A9 R3 C-MA9, A10/AP L7 C-MA10, A11 R7 C-MA11, A12/BC N7 C-MA12, A13 T3, NC_5 M7

BA0 M2 C-MBA0, BA1 N8 C-MBA1, BA2 M3 C-MBA2

CK J7 C-MCK, CK K7, CKE K9 C-MCKE

CS L2, ODT K1 C-MODT, RAS J3 C-MRASB, CAS K3 C-MCASB, WE L3 C-MWEB

RESET T2 C-MRESETB

R333 10K VCC1.5V_U3_DDR

DQSL F3 C-MDQSL, DQSL G3 C-MDQSLB

DQSU C7 C-MDQSU, DQSU B7 C-MDQSUB

DML E7 C-MDML, DMU D3 C-MDMU

DQL0 E3 C-MDQL0, DQL1 F7 C-MDQL1, DQL2 F2 C-MDQL2, DQL3 F8 C-MDQL3, DQL4 H3 C-MDQL4, DQL5 H8 C-MDQL5, DQL6 G2 C-MDQL6, DQL7 H7 C-MDQL7

DQU0 D7 C-MDQU0, DQU1 C3 C-MDQU1, DQU2 C8 C-MDQU2, DQU3 C2 C-MDQU3, DQU4 A7 C-MDQU4, DQU5 A2 C-MDQU5, DQU6 B8 C-MDQU6, DQU7 A3 C-MDQU7

EAN61829001

IC301-*2

H5TQ1G63DFR-PBC

FRC_DDR_1600_HYNIX

C-MVREFCA → M8 VREFCA

H1 VREFDQ

L8 ZQ

VDD_1 B2, VDD_2 D9, VDD_3 G7, VDD_4 K2, VDD_5 K8, VDD_6 N1, VDD_7 N9, VDD_8 R1, VDD_9 R9

VDDQ_1 A1, VDDQ_2 A8, VDDQ_3 C1, VDDQ_4 C9, VDDQ_5 D2, VDDQ_6 E9, VDDQ_7 F1, VDDQ_8 H2, VDDQ_9 H9

NC_1 J1, NC_2 J9, NC_3 L1, NC_4 L9, NC_6 T7

VSS_1 A9, VSS_2 B3, VSS_3 E1, VSS_4 G8, VSS_5 J2, VSS_6 J8, VSS_7 M1, VSS_8 M9, VSS_9 P1, VSS_10 T1, VSS_11 T9, VSS_12

VSSQ_1 B1, VSSQ_2 B9, VSSQ_3 D1, VSSQ_4 D8, VSSQ_5 E2, VSSQ_6 E8, VSSQ_7 F9, VSSQ_8 G1, VSSQ_9 G9

A0 N3 C-MA0, A1 P7 C-MA1, A2 P3 C-MA2, A3 N2 C-MA3, A4 P8 C-MA4, A5 P2 C-MA5, A6 R8 C-MA6, A7 R2 C-MA7, A8 T8 C-MA8, A9 R3 C-MA9, A10/AP L7 C-MA10, A11 R7 C-MA11, A12/BC N7 C-MA12, A13 T3, NC_5 M7

BA0 M2 C-MBA0, BA1 N8 C-MBA1, BA2 M3 C-MBA2

CK J7 C-MCK, CK K7, CKE K9 C-MCKE

CS L2, ODT K1 C-MODT, RAS J3 C-MRASB, CAS K3 C-MCASB, WE L3 C-MWEB

RESET T2 C-MRESETB

DQSL F3 C-MDQSL, DQSL G3 C-MDQSLB

DQSU C7 C-MDQSU, DQSU B7 C-MDQSUB

DML E7 C-MDML, DMU D3 C-MDMU

DQL0 E3 C-MDQL0, DQL1 F7 C-MDQL1, DQL2 F2 C-MDQL2, DQL3 F8 C-MDQL3, DQL4 H3 C-MDQL4, DQL5 H8 C-MDQL5, DQL6 G2 C-MDQL6, DQL7 H7 C-MDQL7

DQU0 D7 C-MDQU0, DQU1 C3 C-MDQU1, DQU2 C8 C-MDQU2, DQU3 C2 C-MDQU3, DQU4 A7 C-MDQU4, DQU5 A2 C-MDQU5, DQU6 B8 C-MDQU6, DQU7 A3 C-MDQU7

EAN61857101

IC301-*3

K4B1G1646G-BCH9

FRC_DDR_1333_SS_NEW

C-MVREFCA → M8 VREFCA

H1 VREFDQ

L8 ZQ

VDD_1 B2, VDD_2 D9, VDD_3 G7, VDD_4 K2, VDD_5 K8, VDD_6 N1, VDD_7 N9, VDD_8 R1, VDD_9 R9

VDDQ_1 A1, VDDQ_2 A8, VDDQ_3 C1, VDDQ_4 C9, VDDQ_5 D2, VDDQ_6 E9, VDDQ_7 F1, VDDQ_8 H2, VDDQ_9 H9

NC_1 J1, NC_2 J9, NC_3 L1, NC_4 L9, NC_6 T7

VSS_1 A9, VSS_2 B3, VSS_3 E1, VSS_4 G8, VSS_5 J2, VSS_6 J8, VSS_7 M1, VSS_8 M9, VSS_9 P1, VSS_10 T1, VSS_11 T9, VSS_12

VSSQ_1 B1, VSSQ_2 B9, VSSQ_3 D1, VSSQ_4 D8, VSSQ_5 E2, VSSQ_6 E8, VSSQ_7 F9, VSSQ_8 G1, VSSQ_9 G9

A0 N3 C-MA0, A1 P7 C-MA1, A2 P3 C-MA2, A3 N2 C-MA3, A4 P8 C-MA4, A5 P2 C-MA5, A6 R8 C-MA6, A7 R2 C-MA7, A8 T8 C-MA8, A9 R3 C-MA9, A10/AP L7 C-MA10, A11 R7 C-MA11, A12/BC N7 C-MA12, A13 T3, NC_5 M7

BA0 M2 C-MBA0, BA1 N8 C-MBA1, BA2 M3 C-MBA2

CK J7 C-MCK, CK K7, CKE K9 C-MCKE

CS L2, ODT K1 C-MODT, RAS J3 C-MRASB, CAS K3 C-MCASB, WE L3 C-MWEB

RESET T2 C-MRESETB

DQSL F3 C-MDQSL, DQSL G3 C-MDQSLB

DQSU C7 C-MDQSU, DQSU B7 C-MDQSUB

DML E7 C-MDML, DMU D3 C-MDMU

DQL0 E3 C-MDQL0, DQL1 F7 C-MDQL1, DQL2 F2 C-MDQL2, DQL3 F8 C-MDQL3, DQL4 H3 C-MDQL4, DQL5 H8 C-MDQL5, DQL6 G2 C-MDQL6, DQL7 H7 C-MDQL7

DQU0 D7 C-MDQU0, DQU1 C3 C-MDQU1, DQU2 C8 C-MDQU2, DQU3 C2 C-MDQU3, DQU4 A7 C-MDQU4, DQU5 A2 C-MDQU5, DQU6 B8 C-MDQU6, DQU7 A3 C-MDQU7

EAN61857201

IC301-*4

NT5CB64M16DP-CF

FRC_DDR_1333_NANYA_NEW

C-MVREFCA → M8 VREFCA

H1 VREFDQ

L8 ZQ

VDD_1 B2, VDD_2 D9, VDD_3 G7, VDD_4 K2, VDD_5 K8, VDD_6 N1, VDD_7 N9, VDD_8 R1, VDD_9 R9

VDDQ_1 A1, VDDQ_2 A8, VDDQ_3 C1, VDDQ_4 C9, VDDQ_5 D2, VDDQ_6 E9, VDDQ_7 F1, VDDQ_8 H2, VDDQ_9 H9

NC_1 J1, NC_2 J9, NC_3 L1, NC_4 L9, NC_7 T7

VSS_1 A9, VSS_2 B3, VSS_3 E1, VSS_4 G8, VSS_5 J2, VSS_6 J8, VSS_7 M1, VSS_8 M9, VSS_9 P1, VSS_10 T1, VSS_11 T9, VSS_12

VSSQ_1 B1, VSSQ_2 B9, VSSQ_3 D1, VSSQ_4 D8, VSSQ_5 E2, VSSQ_6 E8, VSSQ_7 F9, VSSQ_8 G1, VSSQ_9 G9

A0 N3 C-MA0, A1 P7 C-MA1, A2 P3 C-MA2, A3 N2 C-MA3, A4 P8 C-MA4, A5 P2 C-MA5, A6 R8 C-MA6, A7 R2 C-MA7, A8 T8 C-MA8, A9 R3 C-MA9, A10/AP L7 C-MA10, A11 R7 C-MA11, A12 N7 C-MA12, NC_6 T3, NC_5 M7

BA0 M2 C-MBA0, BA1 N8 C-MBA1, BA2 M3 C-MBA2

CK J7 C-MCK, CK K7, CKE K9 C-MCKE

CS L2, ODT K1 C-MODT, RAS J3 C-MRASB, CAS K3 C-MCASB, WE L3 C-MWEB

RESET T2 C-MRESETB

DQSL F3 C-MDQSL, DQSL G3 C-MDQSLB

DQSU C7 C-MDQSU, DQSU B7 C-MDQSUB

DML E7 C-MDML, DMU D3 C-MDMU

DQL0 E3 C-MDQL0, DQL1 F7 C-MDQL1, DQL2 F2 C-MDQL2, DQL3 F8 C-MDQL3, DQL4 H3 C-MDQL4, DQL5 H8 C-MDQL5, DQL6 G2 C-MDQL6, DQL7 H7 C-MDQL7

DQU0 D7 C-MDQU0, DQU1 C3 C-MDQU1, DQU2 C8 C-MDQU2, DQU3 C2 C-MDQU3, DQU4 A7 C-MDQU4, DQU5 A2 C-MDQU5, DQU6 B8 C-MDQU6, DQU7 A3 C-MDQU7

AR301 22: C-MA9 → C-TMA9, C-MA2 → C-TMA2, C-MA0 → C-TMA0, C-MBA2 → C-TMBA2

AR302 22: C-MA8 → C-TMA8, C-MA6 → C-TMA6, C-MA4 → C-TMA4, C-MBA1 → C-TMBA1

AR303 22: C-MA10 → C-TMA10, C-MA12 → C-TMA12, C-MA1 → C-TMA1, C-MA11 → C-TMA11

AR304 22: C-MA3 → C-TMA3, C-MA5 → C-TMA5, C-MA7 → C-TMA7, C-MRESETB → C-TMRESETB

R307 22: C-MCK → C-TMCK

R308 22: C-MCKB → C-TMCKB

R309 22: C-MCKE → C-TMCKE

R310 22: C-MRASB → C-TMRASB

AR305 22: C-MCASB → C-TMCASB, C-MODT → C-TMODT, C-MWEB → C-TMWEB, C-MBA0 → C-TMBA0

R311 22: C-MDQSL → C-TMDQSL

R312 22: C-MDQSLB → C-TMDQSLB

R313 22: C-MDQSU → C-TMDQSU

R314 22: C-MDQSUB → C-TMDQSUB

R315 22: C-MDMU → C-TMDMU

AR306 22: C-MDQL7 → C-TMDQL7, C-MDQL3 → C-TMDQL3, C-MDQL1 → C-TMDQL1, C-MDML → C-TMDML

AR307 22: C-MDQL0 → C-TMDQL0, C-MDQL2 → C-TMDQL2, C-MDQL6 → C-TMDQL6, C-MDQL4 → C-TMDQL4

R316 22: C-MDQL5 → C-TMDQL5

AR308 22: C-MDQU2 → C-TMDQU2, C-MDQU6 → C-TMDQU6, C-MDQU0 → C-TMDQU0, C-MDQU4 → C-TMDQU4

AR309 22: C-MDQU7 → C-TMDQU7, C-MDQU1 → C-TMDQU1, C-MDQU5 → C-TMDQU5, C-MDQU3 → C-TMDQU3

S7M-PLUS_DivX_MS10

IC101

LGE107DC-RP [S7M+ DIVX/MS10]

C-TMA0 → AE1 FRC_DDR3_A0/DDR2_NC

C-TMA1 → AF16 FRC_DDR3_A1/DDR2_A6

C-TMA2 → AF1 FRC_DDR3_A2/DDR2_A7

C-TMA3 → AE3 FRC_DDR3_A3/DDR2_A1

C-TMA4 → AD14 FRC_DDR3_A4/DDR2_CASZ

C-TMA5 → AD3 FRC_DDR3_A5/DDR2_A10

C-TMA6 → AF15 FRC_DDR3_A6/DDR2_A0

C-TMA7 → AF2 FRC_DDR3_A7/DDR2_A5

C-TMA8 → AE15 FRC_DDR3_A8/DDR2_A2

C-TMA9 → AD2 FRC_DDR3_A9/DDR2_A9

C-TMA10 → AD16 FRC_DDR3_A10/DDR2_A11

C-TMA11 → AD15 FRC_DDR3_A11/DDR2_A4

C-TMA12 → AE16 FRC_DDR3_A12/DDR2_A8

C-TMBA0 → AF3 FRC_DDR3_BA0/DDR2_BA2

C-TMBA1 → AF14 FRC_DDR3_BA1/DDR2_ODT

C-TMBA2 → AD1 FRC_DDR3_BA2/DDR2_A12

C-TMCK → AD13 FRC_DDR3_MCLK/DDR2_MCLK

C-TMCKE → AE14 FRC_DDR3_CKE/DDR2_RASZ

C-TMCKB → AE13 FRC_DDR3_MCLKZ/DDR2_MCLKZ

C-TMODT → AE4 FRC_DDR3_ODT/DDR2_BA1

C-TMRASB → AD5 FRC_DDR3_RASZ/DDR2_WEZ

C-TMCASB → AF4 FRC_DDR3_CASZ/DDR2_CKE

C-TMWEB → AD4 FRC_DDR3_WEZ/DDR2_BA0

C-TMRESETB → AE2 FRC_DDR3_RESETB/DDR2_A3

C-TMDQSL → AF8 FRC_DDR3_DQSL/DDR2_DQS0

C-TMDQSLB → AD9 FRC_DDR3_DQSLB/DDR2_DQSB0

C-TMDQSU → AE9 FRC_DDR3_DQSU/DDR2_DQS1

C-TMDQSUB → AF9 FRC_DDR3_DQSUB/DDR2_DQSB1

C-TMDML → AE11 FRC_DDR3_DML/DDR2_DQ7

C-TMDMU → AF6 FRC_DDR3_DMU/DDR2_DQ11

C-TMDQL0 → AE6 FRC_DDR3_DQL0/DDR2_DQ6

C-TMDQL1 → AF11 FRC_DDR3_DQL1/DDR2_DQ0

C-TMDQL2 → AD6 FRC_DDR3_DQL2/DDR2_DQ1

C-TMDQL3 → AD12 FRC_DDR3_DQL3/DDR2_DQ2

C-TMDQL4 → AE5 FRC_DDR3_DQL4/DDR2_DQ4

C-TMDQL5 → AF12 FRC_DDR3_DQL5/DDR2_NC

C-TMDQL6 → AF5 FRC_DDR3_DQL6/DDR2_DQ3

C-TMDQL7 → AE12 FRC_DDR3_DQL7/DDR2_DQ5

C-TMDQU0 → AE10 FRC_DDR3_DQU0/DDR2_DQ8

C-TMDQU1 → AF7 FRC_DDR3_DQU1/DDR2_DQ14

C-TMDQU2 → AD11 FRC_DDR3_DQU2/DDR2_DQ13

C-TMDQU3 → AD7 FRC_DDR3_DQU3/DDR2_DQ12

C-TMDQU4 → AD10 FRC_DDR3_DQU4/DDR2_DQ15

C-TMDQU5 → AE7 FRC_DDR3_DQU5/DDR2_DQ9

C-TMDQU6 → AF10 FRC_DDR3_DQU6/DDR2_DQ10

C-TMDQU7 → AD8 FRC_DDR3_DQU7/DDR2_DQM1

V_SYNC → FRC_L/DIM 33 R332 → AE8 FRC_DDR3_NC/DDR2_DQM0

R317 820 S7M-R → Y11 FRC_VSYNC_LIKE

Y19 FRC_TESTPIN

R317-*1 4.7K S7M-PLUS

ACKP/RLV3P/RED[3] W26 → RXBCK+

ACKM/RLV3N/RED[2] W25 → RXBCK-

A0P/RLV0P/RED[9] U26 → RXB0+

A0M/RLV0N/RED[8] U25 → RXB0-

A1P/RLV1P/RED[7] U24 → RXB1+

A1M/RLV1N/RED[6] V26 → RXB1-

A2P/RLV2P/RED[5] V25 → RXB2+

A2M/RLV2N/RED[4] V24 → RXB2-

A3P/RLV4P/RED[1] W24 → RXB3+

A3M/RLV4N/RED[0] Y26 → RXB3-

A4P/RLV5P/GREEN[9] Y25 → RXB4+

A4M/RLV5N/GREEN[8] Y24 → RXB4-

BCKP/TCON13/GREEN[1] AC26 → RXACK+

BCKM/TCON12/GREEN[0] AC25 → RXACK-

B0P/RLV6P/GREEN[7] AA26 → RXA0+

B0M/RLV6N/GREEN[6] AA25 → RXA0-

B1P/RLV7P/GREEN[5] AA24 → RXA1+

B1M/RLV7N/GREEN[4] AB26 → RXA1-

B2P/RLV8P/GREEN[3] AB25 → RXA2+

B2M/RLV8N/GREEN[2] AB24 → RXA2-

B3P/TCON11/BLUE[9] AC24 → RXA3+

B3M/TCON10/BLUE[8] AD26 → RXA3-

B4P/TCON9/BLUE[7] AD25 → RXA4+

B4M/TCON8/BLUE[6] AD24 → RXA4-

CCKP/LLV3P AD23 → RXCCK+

CCKM/LLV3N AE23 → RXCCK-

C0P/LLV0P/BLUE[5] AE26 → RXC0+

C0M/LLV0N/BLUE[4] AE25 → RXC0-

C1P/LLV1P/BLUE[3] AF26 → RXC1+

C1M/LLV1N/BLUE[2] AF25 → RXC1-

C2P/LLV2P/BLUE[1] AE24 → RXC2+

C2M/LLV2N/BLUE[0] AF24 → RXC2-

C3P/LLV4P AF23 → RXC3+

C3M/LLV4N AD22 → RXC3-

C4P/LLV5P AE22 → RXC4+

C4M/LLV5N AF22 → RXC4-

DCKP/TCON5 AD19 → RXDCK+

DCKM/TCON4 AE19 → RXDCK-

D0P/LLV6P AD21 → RXD0+

D0M/LLV6N AE21 → RXD0-

D1P/LLV7P AF21 → RXD1+

D1M/LLV7N AD20 → RXD1-

D2P/LLV8P AE20 → RXD2+

D2M/LLV8N AF20 → RXD2-

D3P/TCON3 AF19 → RXD3+

D3M/TCON2 AD18 → RXD3-

D4P/TCON1 AE18 → RXD4+

D4M/TCON0 AF18 → RXD4-

GPIO0/TCON15/HSYNC/VDD_ODD AB22 → FRC_MODEL_OPT_0

GPIO1/TCON14/VSYNC/VDD_EVEN AB23 → FRC_MODEL_OPT_1

GPIO2/TCON7/LDE/GCLK4 AC23 → FRC_MODEL_OPT_2

GPIO3/TCON6/LCK/GCLK2 AC22 → 2D/3D_CTL

FRC_SPI_CZ AB16 → FRC_/SPI_CS

FRC_GPIO1 AA14 → FRC_CONF0 → R300 33 FRC_L/DIM → L/DIM_SCLK

FRC_SPI1_CK AC15

FRC_GPIO8 Y16 → FRC_CONF1

FRC_SPI_DO AC16 → FRC_SPI_SDO

FRC_SPI1_DI AC14 → R348 33 FRC_L/DIM → L/DIM_MOSI

FRC_SPI_CK AA16 → FRC_SPI_SCK

FRC_SPI_DI AA15 → FRC_SPI_SDI

FRC_I2CS_DA Y10 → R326 22 FRC → I2C_SDA

FRC_I2CS_CK AA11 → R327 22 FRC → I2C_SCL

R335 22 OPT → FRC_SCL

FRC_PWM0 AB15 → FRC_PWM0

FRC_PWM1 AB14 → FRC_PWM1

R334 22 OPT → FRC_SDA

+3.3V_Normal

R342 10K OPT, R338 10K, R316 10K L/DIM_EDGE_32/33

R341 1K LVDS_EXT_URSA5, R339 1K OPT, R337 1K LVDS_S7M-PLUS

R343 1K OPT L/DIM_EDGE_42/47/55

FRC_MODEL_OPT_0

FRC_MODEL_OPT_1

FRC_MODEL_OPT_2

2D/3D_CTL

<U3 CHIP Config>

(FRC_CONF0)

HIGH : I2C ADR = B8

LOW : I2C ADR = B4

(FRC_CONF1,FRC_PWM1, FRC_PWM0)

3'd5 : boot from internal SRAM

3'd6 : boot from EEPROM

3'd7 : boot form SPI flash

+3.3V_Normal

R320 10K OPT, R321 10K, R323 10K, R322 10K OPT

FRC LVDS_S7M-PLUS S7M-PLUS FRC

R319 10K OPT, R325 1K S7M-R, R324 10K OPT, R318 10K FRC_1K

FRC_CONF0

FRC_CONF1

FRC_PWM1

FRC_PWM0

+3.3V_Normal

S7M-PLUS_S_FLASH_2MBIT_WIN

+3.3V_Normal

IC302

W25X20BVSNIG

R349 10K S7M-PLUS, R350 4.7K OPT S7M-PLUS

FRC_/SPI_CS → R329 10 S7M-PLUS

FRC_SPI_SDO → R330 10 S7M-PLUS

1 /CS, 2 DO, 3 /WP, 4 GND, 5 DIO, 6 CLK, 7 HOLD, 8 VCC

$ 0.17

S7M-PLUS R328 10 → FRC_SPI_SCK

S7M-PLUS R327 10 → FRC_SPI_SDI

THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	FRC_DDR	SHEET	3 /

FROM LIPS & POWER B/D



<MODULE PIN MAP>

PIN No	LGD(PSU) or LIPS	CMO10"Lamp (PSU)	AUO 10"Lamp (PSU)	SHARP (PSU)	IPS-@ (PSU)
16	GND	GND	GND	GND	GND
18	INV_ON	A-DIM	INV_ON	INV_ON	INV_ON
20	VBR-A	NC	Err_out	52/60:ERROR 26/32HD:NC	Err_out
22	PWM_DIM	PWM_DIM	NC	26/32/52:PWM 60:NC	NC
24	Err_out	INV_ON	PWM_DIM	26/32/52:GND 60:PWM	PWM_DIM
23	GND	GND	GND	GND	GND

<LED MODULE PIN MAP -> latest update 20100618>

PIN No	LGD LPB / OS LPB	32LE5300-TA CMO10"LED (PSU)	32LE4500-TA AUO 10"LED (PSU)	32LE5300-TA LGD 10"LED (PSU)	
16	NC	NC	NC	NC	
18	INV_ON	INV_ON	INV_ON	INV_ON	
20	NC	err_out --> NC	err_out --> NC	NC	
22	PWM_DIM	NC	NC	PWM_DIM	
24	err_out --> NC	PWM_DIM	PWM_DIM	err_out --> NC	
23	NC	NC	NC	NC	

LGD edge led error-out use or not? checking is necessary...

TP5302 OLP
TP5303 V_SYNC
TP5304 SCAN_BLK2
TP5305 SCAN_BLK1/OPC_OUT
TP5306 OPC_OUT

<Module Inv to Main Pin Connection>

INV <--> MAIN
#11 <--> #24
#12 <--> #18
#13 <--> #20
#14 <--> #22

PANEL_POWER



S7M DDR 1.5V



+2.5V/+1.8V



S7M core 1.26V volt



+5V_USB



THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

ST_3.5V--> 3.375V --> 3.46V
20V-->3.51V --> 3.76V (3.59V)
24V-->3.78V --> 3.92V (3.79V)
12V -->3.58V --> 3.82V (3.68V)
18.5V-->3.5V --> 3.75V (3.59V)

Power_DET



+3.3V_Normal



+5V_Normal

+1.5V_DDR_FRC



SECRET			
LGElectronics			
LG ELECTRONICS			
MODEL	GP2R	DATE	20101023
BLOCK	POWER_LARGE	SHEET	4









2011Y,GP2R, 101125 Update

MODEL OPTION

PIN NAME	PIN NO.	HIGH	LOW
MODEL_OPT_0	8	B/L_LED	B/L_LAMP
MODEL_OPT_1	11	PWM_BUZZ/IIC_LED	PWM_LED
MODEL_OPT_2	30	TOUCH_KEY	TACT_KEY
MODEL_OPT_3	31	GP2	GP3

PWM_BUZZ/IIC_LED :Using IIC for LED Breathing & PWM Buzz
PWM_LED : Using PWM Signal for LED Lighting

MODEL_OPT_0	MODEL_OPT_1	MODEL_OPT_2	MODEL_OPT_3	Description
LOW	LOW	LOW	LOW	LK330/LK430 (for KR/US 10Y EYE-Q Sensor KEY & PWM LED & No Buzz & No LED Blink
LOW	LOW	LOW	HIGH	LK330/LK430/LK530 KEY & PWM LED & No Buzz & No LED Blink
LOW : LED HIGH : LAMP	HIGH	HIGH	LOW	LV25/LV35/LV45/LW45/LV55/LK45/LK55 S/T & HC LED & NO BUZZ & LED Blink
	HIGH	LOW	LOW	TBD IIC LED(09Y IIC Protocol) & No BUZZ
	Low	HIGH	LOW	TBD S/T & IIC LED & No Buzz & LED Blink

2010Y,GP2

MODEL OPTION

PIN NAME	PIN NO.	HIGH	LOW
MODEL_OPT_0	8	B/L_LED	B/L_LAMP
MODEL_OPT_1	11	PWM_BUZZ/IIC_LED	PWM_LED
MODEL_OPT_2	30	TOUCH_KEY	TACT_KEY
MODEL_OPT_3	31	GPIO_LED	NON_GPIO_LED

PWM_BUZZ/IIC_LED : For model that use LED Lighting used IIC
PWM_LED : For model that use LED Lighting used PWM Signal

MODEL_OPT_0	MODEL_OPT_1	MODEL_OPT_2	MODEL_OPT_3	
LOW	LOW	LOW	LOW	LD350/450/550 PWM LED & No Buzz & No LED Blink
HIGH	LOW	HIGH	LOW	19/22/26LE5300/5300 IIC LED & PWM IIC BUZZ
HIGH	HIGH	HIGH	LOW	32/37/42/47/55LE5300 IIC LED & PWM BUZZ
LOW	HIGH	LOW	LOW	LD420 IIC LED(09Y IIC Protocol) & No BUZZ
HIGH	LOW	LOW	HIGH	LE7300 GPIO LED & NO BUZZ

THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET
LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101125
BLOCK	MICOM Rev.4	SHEET	5

CONTROL

IR & LED



THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	IR/CONTROL-L	SHEET	6

USB_DIODES



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	USB_OCP_DIODE	SHEET	7 /

HDMI_1



HDMI_2



SIDE_HDMI



HDMI EEPROM



For CEC



THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	HDMI	SHEET	8

RGB/SPDIF/PC/HP

New Item Development

EARPHONE BLOCK



PC AUDIO



SPDIF OPTIC JACK



RGB PC



THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	RGB/SPDIF/HP	SHEET	9

RS232C



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	RS232C_9PIN	SHEET	10

[51Pin LVDS Connector] (For FHD 60/120Hz)



[41Pin LVDS Connector] (For FHD 120Hz)

[30Pin LVDS Connector] (For HD 60Hz_Normal)



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	LVDS_LARGE	SHEET	11





EAN61828901

IC1201
H5TQ1G63DFR-H9C





S7M-PLUS_DivX_MS10
IC101
LGE107DC-RP [S7M+ DIVX/MS10]





EAN61828901

IC1202
H5TQ1G63DFR-H9C



IC1201-*1
K4B1G1646G-BCH9



IC1202-*1
K4B1G1646G-BCH9



IC1201-*2
NT5CB64M16DP-CF



IC1202-*2
NT5CB64M16DP-CF



THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	DDR_256	SHEET	12 /



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	FLASH 1MB	SHEET	13 /

GP2R_LARGE_TUNER

TU3702
TDTJ-S001D

DVB_1INPUT_H_LGIT

1	ANT_PWR[OPT]
2	BST_CNTL
3	+B
4	NC[RF_AGC]
5	AS
6	SCL
7	SDA
8	NC[IF_TP]
9	S1F
10	NC
11	VIDEO
12	GND
13	1.2V
14	3.3V
15	RESET
16	IF_AGC_CNTL
17	DIF_1
18	DIF_2
19	SHIELD

CN_2INPUT_H_LG3911

TU3701
TDFR-C036D

1	RF_S/W_CNTL
2	BST_CNTL
3	+B1[+5V]
4	NC[RF_AGC]
5	NC_1
6	SCLT
7	SDAT
8	NC_2
9	S1F
10	NC_3
11	VIDEO
12	GND
13	+B2[1.2V]
14	+B3[3.3V]
15	RESET
16	NC_4
17	SCL
18	SDA
19	ERR
20	SYNC
21	VALID
22	MCL
23	D0
24	D1
25	D2
26	D3
27	D4
28	D5
29	D6
30	D7
31	SHIELD

RF_SWITCH_CTL

Pull-up can't be applied because of MODEL_OPT_2

close to TUNER

OPT R3762 0 — CONTROL_ATTEN

close to TUNER

R3705 0 — C3701 0.1uF 16V — RF_SW_OPT

+5V_TU

C3703 100pF 50V

C3704 0.1uF 16V

R3707 0 OPT

C3706 0.1uF 16V

C3702 0.1uF 16V close to TUNER

+1.2V/+1.8V_TU

C3737 100pF 50V

C3738 0.1uF 16V

FULL_NIM C3705 100uF 16V

close to the tuner pin, add,09029

CN C3739 10uF 6.3V

+3.3V_TU

C3707 100pF 50V

C3708 0.1uF 16V

R3732 100

R3733 100K

TUNER_RESET

C3710 0.1uF 16V

OPTION : RF AGC

C3728 0.1uF 16V OPT

C3731 10uF 10V OPT

Q3704 2SC3052 OPT

R3754 10K OPT

FE_AGC_SPEED_CTL
IF_AGC_SEL

BOOSTER : CHINA OPT

L3700 BOOSTER_OPT BLM18PG121SN1D

BOOSTER_OPT R3734 0

Q3701 ISA1530AC1 BOOSTER_OPT

R3737 2.2K

BOOSTER_OPT R3743 10K

Q3702 2SC3052 BOOSTER_OPT

R3745 10K

FE_BOOSTER_CTL
LNA2_CTL

The pull-up/down of LNA2_CTL is depended on MODLE_OPT_1. GPIO must be added for FE_BOOSTER_CTL

C3709 0.01uF 25V BOOSTER_OPT

GPIO must be added.

TU_IIC_NON_ATSC_SANYO

R3740-*1 1K

+3.3V_TU

R3741-*1 1K

TU_IIC_ATSC_SANYO

R3748 1.2K

R3741 1.2K

R3735 33 TU_I2C_NON_FILTER — TU_SCL

R3736 33 TU_I2C_NON_FILTER — TU_SDA

C3713 18pF 50V

C3711 18pF 50V

C3742 20pF 50V

C3743 20pF 50V TU_I2C_FILTER

TU_I2C_NON_FILTER

TU_I2C_FILTER

C3711-*1 20pF 50V TU_I2C_FILTER

C3713-*1 20pF 50V TU_I2C_FILTER

TU_I2C_FILTER R3735-*1 0 COIL

TU_I2C_FILTER R3736-*1 0 COIL

+5V_TU

R3755 470

R3758 82

TU_SIF

R3754 4.7K

Q3705 ISA1530AC1

+5V_TU

R3751 220

R3752 220

TU_CVBS

R3749 0

R3750 1K OPT

Q3703 ISA1530AC1

DEMOD_RESET

This was being applied to the only china demod, so this has to be deleted in both main and ISDB sh

+3.3V_TU

R3704 0 HALF_NIM

IF_AGC_MAIN

should be guarded by ground

R3742 4.7K FULL_NIM

R3744 4.7K FULL_NIM

DEMOD_SCL

DEMOD_SDA

C3712 22pF 50V FULL_NIM

C3714 22pF 50V FULL_NIM

FULL_NIM R3702 100

R3701 100 FULL_NIM

close to IF line

HALF_NIM R3760 0

R3761 0 HALF_NIM

IF_N_MSTAR

IF_P_MSTAR

1. should be guarded by ground
2. No via on both of them
3. Signal Width >= 12mils
Signal to Signal Width = 12mils
Ground Width >= 24mils

Close to the tuner

HALF_NIM_1.2V_BCD

IC3703

AZ1117BH-ADJTRE1

+3.3V_TU

INPUT 3 — 1 ADJ/GND — 2 OUTPUT

R2 HALF_NIM R3767 10

+1.2V/+1.8V_TU

IC3703-*1 AP1117EG-13

IN OUT ADJ/GND

HALF_NIM_1.2V_DIODES

HALF_NIM R3768 1.2K R1

R3703 150 OPT

HALF_NIM R3766 1 1/10W

Please, check multi item! 10/12

C3740 0.1uF 16V HALF_NIM

C3741 10uF 10V HALF_NIM

IC3701

AP2132MP-2.5TRG1 [OPT]

FULL_NIM_BCD R3748-*1 10K

+1.2V/+1.8V_TU 380mA

C3717 0.1uF 16V

R3771 10K FULL_NIM_BCD

R3770 10K FULL_NIM_SEMTEK

R3769 10K FULL_NIM_BCD

+5V_Normal

L3704 FULL_NIM_BCD

PG 1 — EN 2 — VIN 3 — VCTRL 4 — GND 8 — ADJ 7 — VOUT 6 — NC 5 — THERMAL 9

FULL_NIM_SEMTEK R3748 5.1K R1

R3747 9.1K 1005 R2

Vo=0.8*(1+R1/R2)

R3764 0 1/10W FULL_NIM

FULL_NIM C3729 0.1uF 16V

FULL_NIM C3730 10uF 10V

IC3701-*1 SC4215ISTRT

NC_1 1 — FULL_NIM_SEMTEK 2 — EN 3 — VIN 4 — NC_2 — GND 8 — ADJ 7 — VO 6 — NC_3 5

FULL_NIM R3724 0 — FE_TS_SYNC

FULL_NIM R3730 0 — FE_TS_VAL_ERR

FULL_NIM R3731 0 — FE_TS_CLK

FULL_NIM_CHINA R3725 0 — FE_TS_DATA[0]

FULL_NIM R3727 0 — FE_TS_DATA[1]

FULL_NIM R3728 0 — FE_TS_DATA[2]

FULL_NIM R3729 0 — FE_TS_DATA[3]

FULL_NIM R3726 0 — FE_TS_DATA[4]

FULL_NIM R3721 0 — FE_TS_DATA[5]

FULL_NIM R3722 0 — FE_TS_DATA[6]

FULL_NIM_CHINA R3723 0 — FE_TS_DATA[7]

FE_TS_DATA[0-7]

Close to the CI Slot

R3706 0 FULL_NIM_BR

TUNER MULTI-OPTION

TU3702-*1 TDVJ-H101F

TU3702-*3 U0A35AL

GP1_ATSC_1INPUT_H_LGIT

TU3702-*2 TDTR-T036F

NTSC_2INPUT_H_LGIT

GP2R_AU_1INPUT_H_LGIT TU3702-*4 TDTJ-S101D

TU3701-*2 TDFR-H050F

TU3701-*4 TDFR-C236D

THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

+5V_Normal

+5V_TU 200mA — Size change L3702 MLB-201209-0120P-N2 — C3719 22uF 10V — C3724 0.1uF 16V — C3722 22uF 16V — C3726 0.1uF 16V

location movement,0929

+3.3V_TU 60mA — Size change L3703 MLB-201209-0120P-N2 — C3723 22uF 10V — C3725 0.1uF 16V — C3728 22uF 10V — C3727 0.1uF 16V

Add,0929

MODEL	GP2R	DATE	20101023
BLOCK	TUNER_L	SHEET	14

WOOFER AMP





THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	WOOFER NTP	SHEET	15 /



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	AMP NTP	SHEET	16 /

Rear AV





ETHERNET FOR DVB_T2





Full Scart/ Comp1









THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	REAR JACK	SHEET	17 /

SIDE CVBS PHONE JACK
(New Item Development)



SIDE COMPONENT PHONE JACK
(New Item Developmen)



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	SIDE_JACK	SHEET	18

CI Region

* Option name of this page : CI_SLOT (because of Hong Kong)

CI SLOT



CI TS INPUT



CI HOST I/F





CI DETECT



CI POWER ENABLE CONTROL



THE ⚠S SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠S SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	PCMCI	SHEET	20 /

SMD GASKET



THE ⚠ SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠ SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	SMD_GAS	SHEET	20 /



THE ⚠SYMBOL MARK OF THIS SCHEMETIC DIAGRAM INCORPORATES SPECIAL FEATURES IMPORTANT FOR PROTECTION FROM X-RADIATION. FILRE AND ELECTRICAL SHOCK HAZARDS, WHEN SERVICING IF IS ESSENTIAL THAT ONLY MANUFATURES SPECFIED PARTS BE USED FOR THE CRITICAL COMPONENTS IN THE ⚠SYMBOL MARK OF THE SCHEMETIC.

SECRET

LGElectronics

LG ELECTRONICS

MODEL	GP2R	DATE	20101023
BLOCK	L/DIM_LED	SHEET	21


P2100
BAR CODE
BAR CODE
SOFTWARE LABEL
NON-REVERSE
NON-REVERSE
P704
P703
P705
IC1201
IC1202
IC101
IC1102
IC301
P1901 JK1450
P1902
Pb Free Soldering
L*01U (* : A,B,C,D,J.L.T)
EAX63529602(1)
2010.11.20. H.Y.D
JK803
JK3301
JK9901
JK9902
JK9903
TU3701 TU3702
P2402
P2401
P5050
P501
JK1103
JK1102
JK1104
JK1101
JK801
JK802
JK1604
JK1601
JK1602
JK1603
SCL
SDL
GND
KEY1
KEY2
+3.5V
GND
LOGO
IR
GND
+3.3V
BUZZ
R- R+ L- L+

RUBBER
10x10
RUBBER
10x10
J1K604
J1K602
J1K601
J1K803
J1K303
J1K302
J1K301
J1K103
J1K102
J1K101
J1K104
J1U302
J1U303
J1U304
J1K603
J1K605
J1K606
J1K607
J1K608
J1K609
J1K610
J1K611
J1K612
J1K613
J1K614
J1K615
J1K616
J1K617
J1K618
J1K619
J1K620
J1K621
J1K622
J1K623
J1K624
J1K625
J1K626
J1K627
J1K628
J1K629
J1K630
J1K631
J1K632
J1K633
J1K634
J1K635
J1K636
J1K637
J1K638
J1K639
J1K640
J1K641
J1K642
J1K643
J1K644
J1K645
J1K646
J1K647
J1K648
J1K649
J1K650
J1K651
J1K652
J1K653
J1K654
J1K655
J1K656
J1K657
J1K658
J1K659
J1K660
J1K661
J1K662
J1K663
J1K664
J1K665
J1K666
J1K667
J1K668
J1K669
J1K670
J1K671
J1K672
J1K673
J1K674
J1K675
J1K676
J1K677
J1K678
J1K679
J1K680
J1K681
J1K682
J1K683
J1K684
J1K685
J1K686
J1K687
J1K688
J1K689
J1K690
J1K691
J1K692
J1K693
J1K694
J1K695
J1K696
J1K697
J1K698
J1K699
J1K700
J1K701
J1K702
J1K703
J1K704
J1K705
J1K706
J1K707
J1K708
J1K709
J1K710
J1K711
J1K712
J1K713
J1K714
J1K715
J1K716
J1K717
J1K718
J1K719
J1K720
J1K721
J1K722
J1K723
J1K724
J1K725
J1K726
J1K727
J1K728
J1K729
J1K730
J1K731
J1K732
J1K733
J1K734
J1K735
J1K736
J1K737
J1K738
J1K739
J1K740
J1K741
J1K742
J1K743
J1K744
J1K745
J1K746
J1K747
J1K748
J1K749
J1K750
J1K751
J1K752
J1K753
J1K754
J1K755
J1K756
J1K757
J1K758
J1K759
J1K760
J1K761
J1K762
J1K763
J1K764
J1K765
J1K766
J1K767
J1K768
J1K769
J1K770
J1K771
J1K772
J1K773
J1K774
J1K775
J1K776
J1K777
J1K778
J1K779
J1K780
J1K781
J1K782
J1K783
J1K784
J1K785
J1K786
J1K787
J1K788
J1K789
J1K790
J1K791
J1K792
J1K793
J1K794
J1K795
J1K796
J1K797
J1K798
J1K799
J1K800
J1K801
J1K802
J1K803
J1K804
J1K805
J1K806
J1K807
J1K808
J1K809
J1K810
J1K811
J1K812
J1K813
J1K814
J1K815
J1K816
J1K817
J1K818
J1K819
J1K820
J1K821
J1K822
J1K823
J1K824
J1K825
J1K826
J1K827
J1K828
J1K829
J1K830
J1K831
J1K832
J1K833
J1K834
J1K835
J1K836
J1K837
J1K838
J1K839
J1K840
J1K841
J1K842
J1K843
J1K844
J1K845
J1K846
J1K847
J1K848
J1K849
J1K850
J1K851
J1K852
J1K853
J1K854
J1K855
J1K856
J1K857
J1K858
J1K859
J1K860
J1K861
J1K862
J1K863
J1K864
J1K865
J1K866
J1K867
J1K868
J1K869
J1K870
J1K871
J1K872
J1K873
J1K874
J1K875
J1K876
J1K877
J1K878
J1K879
J1K880
J1K881
J1K882
J1K883
J1K884
J1K885
J1K886
J1K887
J1K888
J1K889
J1K890
J1K891
J1K892
J1K893
J1K894
J1K895
J1K896
J1K897
J1K898
J1K899
J1K900
J1K901
J1K902
J1K903
J1K904
J1K905
J1K906
J1K907
J1K908
J1K909
J1K910
J1K911
J1K912
J1K913
J1K914
J1K915
J1K916
J1K917
J1K918
J1K919
J1K920
J1K921
J1K922
J1K923
J1K924
J1K925
J1K926
J1K927
J1K928
J1K929
J1K930
J1K931
J1K932
J1K933
J1K934
J1K935
J1K936
J1K937
J1K938
J1K939
J1K940
J1K941
J1K942
J1K943
J1K944
J1K945
J1K946
J1K947
J1K948
J1K949
J1K950
J1K951
J1K952
J1K953
J1K954
J1K955
J1K956
J1K957
J1K958
J1K959
J1K960
J1K961
J1K962
J1K963
J1K964
J1K965
J1K966
J1K967
J1K968
J1K969
J1K970
J1K971
J1K972
J1K973
J1K974
J1K975
J1K976
J1K977
J1K978
J1K979
J1K980
J1K981
J1K982
J1K983
J1K984
J1K985
J1K986
J1K987
J1K988
J1K989
J1K990
J1K991
J1K992
J1K993
J1K994
J1K995
J1K996
J1K997
J1K998
J1K999
J1K1000

LG Electronics Inc.

1. Power-up boot check



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

2. Digital TV Video



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

3. Analog TV Video



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

4. AV Video



5. Component Video



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

6. RGB Video



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

7. HDMI Video



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

8. All Source Audio



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

9. Digital TV Audio



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

10. Analog TV Audio



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

11. AV Audio



12. Component Audio



13. RGB Audio



Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes

LGE Internal Use Only

GP3 Carry Over 모델 Block Diagram

LG Electronics/ LCD TV 연구소
연구 1실 / AT1 그룹

Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes



※ GP2 대비 변경부품 : 보라색 font

Copyright ⓒ 2011 LG Electronics. Inc. All right reserved.
Only for training and service purposes